

Domaća zadaća br.12

Pojednostavni logičke izraze:

1. $A \cdot 1 + \bar{A} \cdot 0 =$

2. $\bar{A} \cdot 1 + A \cdot A =$

3. $\bar{A} \cdot (A + B) =$

4. $A \cdot (\bar{A} + B) =$

5. $A \cdot 0 + \bar{A} \cdot 1 =$

6. $\bar{A} \cdot \bar{A} + A \cdot 1 =$

7. $A \cdot \bar{A} + 1 =$

8. $A \cdot A + \bar{A} \cdot 0 =$

9. $A \cdot \overline{\bar{A} + B} =$

10. $A \cdot \bar{A} + A \cdot 1 =$

11. $A + \overline{(A \cdot B)}$

12. $\overline{\bar{A} + \bar{A}}$

13. $\overline{\bar{A} \cdot \bar{A}}$

14. $\bar{A} \cdot 1 + \bar{A}$

15. $A \cdot A + \bar{A} \cdot 1 =$